

Specifications Benq MW853UST



Model	MW853UST
Projection System	DLP
Native Resolution	WXGA(1280*800)
Brightness (ANSI Lumens)	3200AL
Contrast Ratio	10,000:1
Display Color	1.07 Billion Colors
Lens	F2.5,f=5.1mm
Aspect Ratio	Native 16:10 (5 aspect ratio selectable)
Throw Ratio	0.35
Image Size (Diagonal)	Optimize 80"-100" / Max up to 300"
Zoom Ratio	Fix
Lamp Type	230W
Lamp Mode (Normal/Economic)*	4000/5000/7000 hours
Keystone Adjustment	1D, Vertical \pm 40 degrees

Projection Offset**	140%-148% ($\pm 5\%$)
Resolution Support	VGA(640 x 480) to UXGA(1600 x 1200)
Horizontal Frequency	15~102KHz
Vertical Scan Rate	23~120Hz
HDTV Compatibility	480i, 480p, 576i, 576p, 720p, 1080i, 1080p
Video Compatibility	NTSC, PAL, SECAM
Interface	Computer in (D-sub 15pin) x 2(Shared with component) Monitor out (D-sub 15pin) x 1 Composite Video in (RCA) x 1 S-Video in (Mini DIN 4pin) x 1 HDMI x 1 Audio in (Mini Jack) x 1 Audio out (Mini Jack) x 1 Audio L/R *1 Speaker 10W x 2 USB (Type mini B) x 1 (PointWrite interactive module) USB (Type B) x1 (FW download) RJ45 x1 (LAN control) RS232 (DB-9pin) x 1 IR Receiver x1 (Front)
Dimensions (W x H x D mm)	373.3*287.5*130.2mm (w/o Mirror) 373.3*287.5*201mm(w Mirror)
Weight	5Kg (wall mount base plate excluded)
Audible Noise (Normal/Economic Mode)	33/29 dBA (Normal/Economic mode)
Power Supply	AC100 to 240 V, 50 to 60 Hz
Power Consumption	typical 290W, stanby power <0.5W
On-Screen Display Languages	Arabic/Bulgarian/ Croatian/ Czech/ Danish/ Dutch/ English/ Finnish/ French/ German/ Greek/ Hindi/ Hungarian/ Italian/ Indonesian/ Japanese/ Korean/ Norwegian/ Polish/ Portuguese/ Romanian/ Russian/ Simplified Chinese/Spanish/ Swedish/ Turkish/ Thai/ Traditional Chinese (28 Languages)
Picture Modes	Dynamic/Presentation/sRGB/Cinema/(3D)/User 1/User 2
Accessories	Remote Control w/ Battery RCE012

(Standard)	Power Cord (by region) 2.9M User Manual CD *1 Quick Start Guide *1 Warranty Card (by region) *1 VGA(D-sub 15pin) Cable *1 Dust filter(C SKU) *1 Wall mount kit (installation guide) *1
Accessories (Optional)	Spare Lamp Kit 5J.J8M05.011
Environmental Notice	Lamp in this product contains mercury. To dispose of the product or used lamps, consult your local environment authorities for regulations or see www.lamprecycle.org .



- **Address** : Office No. D-4, Ambika Darshan Building, Chittabhai Patel Road, Behind Sapan Nikhil Classes, Ahead of Kandivali Bus Depot, Kandivali (E), Mumbai-400101.
- **Phone No**: +022-28460505 (50 lines)
- **Email**: itsolutions@varay.co.in